


Rillenkugellager, metrisch (Auswahl)

Abmessungen in mm



Type	d	D	B/B1	Type	d	D	B/B1	Type	d	D	B/B1*
Rillenkugellager über 10mm Bohrung (Standard Serie):								* B1= Breite für 2Z od. 2RS			
6000	10	26	8	6200	10	30	9	6300	10	35	11
6001	12	28	8	6201	12	32	10	6301	12	37	12
6002	15	32	9	6202	15	35	11	6302	15	42	13
6003	17	35	10	6203	17	40	12	6303	17	47	14
6004	20	42	12	6204	20	47	14	6304	20	52	15
6005	25	47	12	6205	25	52	15	6305	25	62	17
6006	30	55	13	6206	30	62	16	6306	30	72	19
6007	35	62	14	6207	35	72	17	6307	35	80	21
6008	40	68	15	6208	40	80	18	6308	40	90	23
6009	45	75	16	6209	45	85	19	6309	45	100	25
6010	50	80	16	6210	50	90	20	6310	50	110	27
6011	55	90	18	6211	55	100	21	6311	55	120	29
6012	60	95	18	6212	60	110	22	6312	60	130	31
6013	65	100	18	6213	65	120	23	6313	65	140	33
6014	70	110	20	6214	70	125	24	6314	70	150	35

Rillenkugellager unter 10mm Bohrung (Miniatur Lager):

68/06	0,6	2,5	1	684zzB35	3,5	9	/4	MR 117	7	11	2,5/3
681	1	3	1	MR 74	4	7	2/2,5	MR 137	7	13	3/4
MR 31	1	3	1,5	MR 84	4	8	2/3	687	7	14	3,5/5
691	1	4	1,6/2	684	4	9	2,5/4	697	7	17	5
MR 41X	1,2	4	1,8/2,5	MR 104	4	10	3/4	607	7	19	6
681 X	1,5	4	1,2/2	694	4	11	4	627	7	22	7
691 X	1,5	5	2/2,6	604	4	12	4	637	7	26	9
601 X	1,5	6	2,5/3	624	4	13	5	MR 128	8	12	2,5/3,5
672	2	4	1,2/2	634	4	16	5	MR 148	8	14	3,5/4
682	2	5	1,5/2,3	MR 85	5	8	2/2,5	688	8	16	4/5
MR 52	2	5	2/2,5	MR 95	5	9	2,5/3	698	8	19	6
692	2	6	2,3/3	MR 105	5	10	3/4	608 W6	8	22	6
MR 62	2	6	2,5	685	5	11	3/5	608	8	22	7
MR 72	2	7	2,5/3	MR 115	5	11	4	628	8	24	8
602	2	7	2,8/3,5	695	5	13	4	638	8	28	9
682 X	2,5	6	1,8/2,6	605	5	14	5	679	9	14	3
692 X	2,5	7	2,5/3,5	625	5	16	5	689	9	17	4/5
MR 82X	2,5	8	2,5	635	5	19	6	699	9	20	6
602 X	2,5	8	2,8/4	MR 106	6	10	2,5/3	609	9	24	7
MR 63	3	6	2/2,5	MR 126	6	12	3/4	629	9	26	8
683	3	7	2/3	686	6	13	3,5/5	639	9	30	10
MR 83	3	8	2,5	696 619/6	6	15	5				
693	3	8	3/4	616 696A	6	16	5				
MR 93	3	9	2,5/4	MR 166	6	16	6				
603	3	9	3	606	6	17	6				
623	3	10	4	626	6	19	6				
633	3	13	5	636	6	22	7				

Type	d	D	B/B1	Type	d	D	B/B1	Type	d	D	B/B1
Rillenkugellager über 10mm Bohrung (breite Serien):								*B1= Breite für 2Z od. 2RS			
63000	10	26	11	62200	10	30	14	62300	10	35	17
63001	12	28	12	62201	12	32	14	62301	12	37	17
63002	15	32	13	62202	15	35	14	62302	15	42	17
63003	17	35	14	62203	17	40	16	62303	17	47	19
63004	20	42	16	62204	20	47	18	62304	20	52	21
63005	25	47	16	62205	25	52	18	62305	25	62	24
63006	30	55	19	62206	30	62	20	62306	30	72	27
63007	35	62	20	62207	35	72	23	62307	35	80	31
63008	40	68	21	62208	40	80	23	62308	40	90	33
63009	45	75	23	62209	45	85	23	62309	45	100	36
63010	50	80	23	62210	50	90	23	62310	50	110	40

.... breite Serie Fortsetzung

63302	15	42	19
63303	17	47	22
63304	20	52	22.2
63305	25	62	25.4
63306	30	72	30.2
63307	35	80	34.9
63308	40	90	36.5
63309	45	100	39.7

Rillenkugellager über 10mm Bohrung (schmale Serien - Dünnringlager):

6700	10	15	3(4)	61800	10	19	5	63800	10	19	7
6701	12	18	4	61801	12	21	5	63801	12	21	7
6702	15	21	4	61802	15	24	5	63802	15	24	7
6703	17	23	4	61803	17	26	5	63803	17	26	7
6704	20	27	4	61804	20	32	7	63804	20	32	10
6705	25	32	4	61805	25	37	7	63805	25	37	10
6706	30	37	4	61806	30	42	7	63806	30	42	10
6707	35	44	5	61807	35	47	7				
6708	40	50	6	61808	40	52	7				
6709	45	55	6	61809	45	58	7				
6710	50	62	6	61810	50	65	7				
61900	10	22	6	16100	10	28	8				
				16101	12	30	8				
61901	12	24	6	16001	12	28	7				
61902	15	28	7	16002	15	32	8				
61903	17	30	7	16003	17	35	8				
61904	20	37	9	16004	20	42	8				
61905	25	42	9	16005	25	47	8				
61906	30	47	9	16006	30	55	9				
61907	35	55	10	16007	35	62	9				
61908	40	62	12	16008	40	68	9				
61909	45	68	12	16009	45	75	10				
61910	50	72	12	16010	50	80	10				

Rev. 2019.10

Ihr starker Partner für E-Motoren, Getriebe, Frequenzumformer, Kugellager, Antriebselemente, Keilriemen, Kupplungen, Keilriemenscheiben, Kettenräder, Wälzlager, Ventilatoren

Dieses Dokument ist auf unserer Homepage veröffentlicht.